V1.0 Nov, 2022



IGPS-RX884GTP+

Industrial advanced Layer 3 20-port managed Gigabit Ethernet switch with 8x10/100/1000Base-T(X) ports, 8x10/100/1000Base-T(X) P.S.E. ports and 4x1G/10GBase-X ports, SFP+ socket

Features

- Support 8-ports IEEE 802.3af/at compliant PoE and total power budget is 100W with maximum 30W per port
- Support routing protocols Static routing, RIP v1/v2, OSPF, PIM-SM, PIM-DM, VRRP
- ➤ IEEE 802.1AS for timing & Synchronization
- Support O-Ring (recovery time < 30ms) and MSTP(RSTP/STP compatible) for Ethernet Redundancy</p>
- O-Chain allow multiple redundant network rings
- Provided HTTPS/SSH protocol to enhance network security
- Support SNTP client
- Support application-based QoS management
- Support DOS/DDOS auto prevention
- IGMP v2/v3 (IGMP snooping support) for filtering multicast traffic
- Support SNMP v1/v2c/v3 & RMON & 802.1Q VLAN Network Management
- Support ACL and 802.1x User Authentication for security
- Support 12K Bytes Jumbo Frame
- Multiple notification for warning of unexpected event
- Web-based ,Telnet, Console (CLI),
- Rigid IP-30 housing design
- > DIN-Rail and wall mounting enabled







Introduction


IGPS-RX884GTP+ advanced Layer 3 managed redundant ring Ethernet switch with 8x10/100/1000Base-T(X) ports + 8x10/100/1000Base-T(X) P.S.E ports and 4x1G/10GBase-X SFP ports. The IGPS-RX884GTP+ supports routing protocols such as static routing, RIP v1/v2, OSPF and PIM which are suitable for large scale network environment. The hardware Layer 3 switch is optimized to transmit data as fast as Layer-2 switches. With completely support of Ethernet Redundancy protocol, **O-Ring** (recovery time < 30ms) and MSTP (RSTP/STP compatible) can protect your mission-critical applications from network interruptions or temporary malfunctions with its fast recovery technology. And support wide operating temperature from -40 °C to 75°C. IGPS-RX884GTP+ can also be managed centralized and convenient by Open-Vision, as well as the Web-based interface, Telnet and console (CLI) configuration. Therefore, the switch is one of the most reliable choice for highly-managed and Fiber Ethernet application.


- O-Ring: O-Ring is ORing's proprietary redundant ring technology, with recovery time of less 30 milliseconds. The O-Ring redundant ring technology can protect mission-critical application from network interruptions or temporary malfunction with its fast recover technology.
- O-Chain: O-Chain is the revolutionary network redundancy technology that provides the add-on network redundancy topology for any backbone network, O-Chain allows multiple redundant network rings of different redundancy protocols to join and function together as a larger and more robust compound network topology. O-Chain providing ease-of-use while maximizing fault-recovery swiftness, flexibility, compatibility, and cost-effectiveness in one set of network redundancy topology.


Dimension











change without notice.

Specifications

ORing Switch Model	IGPS-RX884GTP+
Physical Ports	
10/100/1000Base-T(X) Ports in RJ45	_
Auto MDI/MDIX	8
10/100/1000Base-T(X) P.S.E Ports in	8
RJ45 Auto MDI/MDIX	8
1G/2.5G/10GBase-X with SFP+ port	4
Technology	
	IEEE 802.3 for 10Base-T
	IEEE 802.3u for 100Base-TX and 100Base-FX
	IEEE 802.3ab for 1000Base-T
	IEEE 802.3z for 1000Base-X
	IEEE 802.3ae for 10Gigabit Ethernet
	IEEE 802.3x for Flow control
	IEEE 802.3ad for LACP (Link Aggregation Control Protocol) IEEE 802.1p for COS (Class of Service)
Ethernet Standards	IEEE 802.1Q for VLAN Tagging
Ethernet Standards	IEEE 802.1w for RSTP (Rapid Spanning Tree Protocol)
	IEEE 802.1s for MSTP (Multiple Spanning Tree Protocol)
	IEEE 802.1x for Authentication
	IEEE 802.1AB for LLDP (Link Layer Discovery Protocol)
	IEEE 802.1AS for Timing and Synchronization
	IEEE 802.1Qat for Stream Reservation
	IEEE 802.1Qav for Forwarding and Queuing Enhancements for Time-Sensitive Streams
	IEEE 802.3af/at PoE specification
MAC Table	16k
Priority Queues	8
Packet Buffer	2MB
Flash Memory	512Mbits
DRAM Size	8Gbits
Jumbo frame	Up to 12K Bytes
Processing	Store-and-Forward
	Switching latency: 7 us
	Switching bandwidth: 112Gbps
	Throughput (packet per second): 83.32Mpps@64Bytes packet
Switch Properties	Max. Number of Available VLANs: 4095
	VLAN ID Range: VID 1 to 4094
	IGMP multicast groups: 128 for each VLAN
	Port rate limiting: User Define
	Enable/disable ports, MAC based port security
	Port based network access control (802.1x)
	MAC-based authentication(802.1x)
Security Features	VLAN (802.1Q) to segregate and secure network traffic
	Radius centralized password management
	SNMPv3 encrypted authentication and access security Web and CLI authentication and authorization
	IP source quard
	Https / SSH enhance network security
	STP/RSTP/MSTP (IEEE 802.1D/w/s)
Software Features	Redundant Ring (O-Ring) with recovery time less than 30ms
	TOS/Diffserv supported
	Quality of Service (802.1p) for real-time traffic
	VLAN (802.1Q) with VLAN tagging
	IGMP Snooping
	Application-based QoS management
	DOS/DDOS auto prevention
	Port configuration, status, statistics, monitoring, security
	Port mirroring
	DHCP Server/Client/Relay
	SNTP Client
	O-Ring
Network Redundancy	O-Chain

	MSTP/RSTP/STP		
	Unicast Routing		
Routing Protocols	- Static routing, RIP v1/v2, OSPF		
	Multicast Routing		
	-PIM-SM, PIM-DM,		
	Routing Redundancy		
	-VRRP		
	PoE configuration PoE Status		
PoE management	PoE Scheduling(turn on/off the PoE device)		
	Auto-Ping check(Reboot PDs if there is no responses)		
RS-232 Serial Console Port	RS-232 in DB9 connector with console cable. 115200bps, 8, N, 1		
LED indicators			
Power Indicator (PWR)	Green: Power LED x 3		
Ring Master Indicator (R.M.)	Green: Indicates that the system is operating in O-Ring Master mode		
	Green : Indicates that the system operating in O-Ring mode		
O-Ring Indicator (Ring)	Green Blinking: Indicates that the Ring is broken.		
Fault Indicator (Fault)	Amber : Indicate unexpected event occurred		
10/100/1000Base-T(X) RJ45 Port	Upper for Link/Act indicator, Green for Link/Act indicator		
Indicator	Lower for speed indicator, Green for 1000Mbps, Amber for 100Mbps, Off-light for 10Mbps		
10/100/1000Base-T(X) RJ45 P.S.E	Upper for Link/Act indicator, Green for Link/Act indicator		
Port Indicator	Lower for PoE indicator, Green for PoE enable		
1G/2.5G/10GBase-X SFP+ Port Indicator	Green for port Link/Act.		
Fault contact			
Relay	Relay output to carry capacity of 1A at 24VDC		
•	Relay output to carry capacity of IA at 244000		
Power			
Redundant Input power	Dual DC inputs 50~57VDC on 6-pin terminal block		
Power consumption (Typ.)	20W(without PoE)		
Total PoE power budget	100W@75°c/180W@60°C		
Overload current protection	Present		
Reverse Polarity Protection	Present		
Physical Characteristic			
Enclosure	IP-30		
Dimension (W x D x H)	116 x 170 x 180 mm		
Weight (g)	2,8Kg		
Environmental			
Storage Temperature	-40 to 85°C (-40 to 185°F)		
Operating Temperature	-40 to 75°C		
Operating Humidity	5% to 95% Non-condensing		
Regulatory approvals			
EMC	CE EMC (EN 55035, EN 55032), FCC Part 15 B		
EMI	EN 55032, CISPR32, EN 61000-3-2, EN 61000-3-3, FCC Part 15 B class A		
EMS	IEC/EN 61000-4-2 (ESD), IEC/EN 61000-4-3 (RS), IEC/EN 61000-4-4 (EFT), IEC/EN 61000-4-5 (Surge),		
	IEC/EN 61000-4-6 (CS), IEC/EN 61000-4-8(PFMF)		
Shock Free Fall	IEC60068-2-27		
Free Fall	IEC60068-2-31		
Vibration	IEC60068-2-6		
MTBF	252,899 hrs		
Warranty	5 years		

Ordering Information

	Model Name	Description
Available Model	IGPS-RX884GTP+	Industrial advanced Layer 3 20-port managed Gigabit Ethernet switch with
		8x10/100/1000Base-T(X) ports, 8x10/100/1000Base-T(X) P.S.E. ports and
		4x1G/10GBase-X ports, SFP+ socket

Packing List

- IGPS-RX884GTP+
- ORing Tool CD x 1
- Quick Installation Guide x 1

- DIN-Rail Kit x 1
- Wall-mount Kit x 2
- Console Cable x 1

Optional Accessories

Open-Vision M500 : Powerful Network

Management Windows Utility Suit, 500 IP devices

• DR/SDR/NDR series : DIN-Rail power supply

SFP 1G series : 1Gbps SFP optical transceiver

SFP 10G series : 10Gbps SFP optical transceiver